



Configuration:

LA-344 Replacement Mounting Hardware (For LT-84, LA-141 only)

Product Overview:

Omni-directional wall, ceiling or table mounting bracket for LT-84 ListenIR Transmitter/Radiator Combo and LA-141 ListenIR Expansion Radiator. This mounting system is modular and the finished lengths can be adjusted to 2 in. (5.08 cm), 4 in. (10.16 cm), or 6 in. (15.24 cm).

This mount features a 190° tilt and a 360° turn and rotation with locking ring. The mount angle can easily be adjusted via a thumb knob or can be made tamper-resistant with the included set screw adjusting option.

Highlights:

- Versatile mounting for wall, ceiling, or table
- Modular system allows for multiple mount configurations
- 190° tilt, 360° turn, and 360° rotation with locking ring
- Finished lengths of 2 in. (5.08 cm), 4 in. (10.16 cm), or 6 in. (15.24 cm)

- Includes:** One (1) Wall Base
 One (1) Ceiling T-Bar Base
 One (1) Black Vinyl Base Cover
 Two (2) Shafts
 One (1) Adjustable Head with Locking Ring
 One (1) Alan Head Tamper Resistant Set Screw
 One (1) Alan Wrench
 One (1) 1/4 x 20 all-thread

Product Specification: Replacement Mounting Hardware (For LT-84, LA-141 only)	
Physical	
Shipping Weight	1.0 lbs (0.5 kg)
Base 2	T-Bar Clip for drop ceiling rails, 1/4-20 stud
Base 1	2" (50.8 mm) round base with four 0.188" (4.8mm) holes on 1.6" (40.6mm) bolt circle for solid surface mounting, 1/4-20 stud
Base Cover	Matching black vinyl cover adds a finished look to either base
Shafts	Two aluminum shafts, 0.5" (12.7mm) diameter, 2" (50.8mm) long, black, 1/4-20 stud
Adjustable Head	Fully adjustable with locking ring, 190° Tilt, 360° Turn and 360° Rotation)
Finished Lengths	2" (50.8mm), 4" (101.6mm) or 6" (152.4mm) long mount
Unit Weight	0.3 lbs (166.5g)
Maximum Load Weight	3 lbs (1.36 kg)