



GT 400R



The Clockaudio GT 400R is a portable lightweight receiver. It is easy to set up and use and operates over a distance of 100 meters. When fully charged the GT 400R can be used for 8-10 hours. The receiver is suitable for in and outdoor use.

Frequency Range 863-870MHz

Not available in the US and Canada.

Description

The Clockaudio GT 400R is a portable lightweight receiver. It is easy to set up and use and operates over a distance of 100 meters. When fully charged the GT 400R can be used for 8-10 hours. The receiver is suitable for in and outdoor use.

- Portable, wireless listening, easy to set up and use. No installation is required.
- 32 switchable frequencies in Channel 10 (863-870MHz).
- LCD channel display to show the selected channel by up and down button, frequency, battery condition and error code.
- An unlimited number of receivers can be used with one transmitter GT 400T.
- Pocket size, rechargeable wireless receiver.
- Fully charged batteries provide 8-10 hours use.
- GTE-10 ear piece included.
- Internal Loudspeaker.
- GT 400R receiver includes Aux. Output for connecting an amplifier or active speaker form a wireless receiver system and 3.5mm jack for use with an earphone GTE-10.

For 'Glossary of Terms' [Click Here](#)

Specification

Technical	
Receiving Mode	PLL Single-channel.
RF Spurious Rejection	>55db
IMD Rejection	>55db
Double Intermediate	130.06MHz / 10.7MHz
Audio Level	12V
AUX Output	300 mV

Earphone Connector	3.5mm
Battery Life	(Lithium) 8-10 Hours
Carrier Frequency Range	863-870MHz